

	A	B	C	D	E	F	G	H
1					TIDA-01215 DAC38RF8x EVM	Revision: E		
2	Item	Quantity	Reference	Note	Part	Part Number	Manufacturer	Foot Print
3	1	9	C1,C54,C60,C313,C385,C427,C440,C441,C447		0.01uF	GRM155R71H103KA88D	MURATA	402
4	2	0	C2,C3,C37,C44,C45,C366,C449,C450	DNI	.1uF	GRM033R61A104KE15D	MURATA	201
5	3	32	C5,C6,C8,C9,C10,C11,C13,C14,C16,C17,C18,C19,C21,C22,C23,C24,C28,C29,C31,C32,C38,C42,C43,C46,C47,C48,C49,C50,C360,C365,C443,C448		.1uF	GRM033R61A104KE15D	MURATA	201
6	4	3	C25,C333,C334		0.01uF	GRM033R71A103KA01D	MURATA	201
7	5	1	C27		.001uF	04025C102JAT2A	AVX	402
8	6	1	C30		.68uF	C1005X750J684K050BC	TDK	402
9	7	1	C33		3900pF	0201ZD392KAT2A	AVX	201
10	8	1	C34		47pF	GRM0335C1E470JA01D	MURATA	201
11	9	49	C35,C36,C107,C108,C111,C112,C115,C116,C117,C118,C122,C123,C124,C125,C126,C127,C128,C129,C132,C133,C136,C137,C140,C141,C144,C145,C148,C149,C152,C153,C156,C157,C160,C161,C164,C165,C167,C169,C170,C171,C174,C175,C176,C177,C375,C407,C438,C439,C446		.1uF	C0603X751A104K030BC	TDK	201
12	10	1	C39		100pF	C1005COG1H101J050BA	TDK	402
13	11	1	C40		2200pF	ECJ-0EB1E222K	Panasonic	402
14	12	1	C41		10pF	GRM1555C1H100J201D	MURATA	402
15	13	1	C51		12pF	C0603COG1E120G030BG	TDK	201
16	14	2	C52,C58		1uF	GRM155R61A105KE15D	MURATA	402
17	15	24	C53,C59,C61,C65,C67,C80,C81,C82,C83,C84,C85,C86,C87,C223,C247,C260,C312,C314,C364,C368,C369,C389,C402,C433		.1uF	GRM155R71C104KA88D	MURATA	402
18	16	5	C55,C56,C57,C63,C64		1uF	C1608X7R1E105K080AB	TDK	603
19	17	1	C62		10uF	C1608X5R1A106K	TDK	603
20	18	3	C66,C68,C442		4.7uF	C0603C475K8PACTU	Kemet	603
21	19	28	C70,C72,C222,C236,C241,C244,C250,C254,C255,C258,C262,C268,C271,C274,C282,C291,C294,C300,C304,C308,C322,C387,C390,C393,C415,C418,C420,C445		10uF	CL21B106K0QNNNE	SAMSUNG	805
22	20	11	C71,C225,C248,C259,C307,C315,C318,C320,C388,C432,C435		1.0uF	C1608X7R1E105K	Yageo	603
23	21	2	C73,C75		100uF	C1206C107M9PACTU	KEMET	1206
24	22	1	C74		10uF	GRM31CR61E106KA12L	MURATA	1206
25	23	0	C76,C77	DNI	22pF	04025A220KAT2A	AVX	402
26	24	2	C78,C79		27pF	CC0402JRNPO9BN270	Yageo	402
27	25	18	C106,C110,C114,C119,C131,C135,C139,C143,C147,C151,C155,C159,C163,C168,C218,C220,C373,C376		10uF	C1608X750J106M080AC	TDK CORP	603
28	26	1	C120		1uF	02016D105MAT2A	AVX	201
29	27	2	C179,C400		.1uF	GRM155R71C104KA88D	Samsung	402
30	28	2	C221,C303		47uF	GRM32ER71A476KE15L	MURATA	1210
31	29	5	C224,C384,C395,C428,C429		22uF	GRM31CR71A226KE15L	MURATA	1206
32	30	19	C237,C242,C245,C251,C256,C263,C269,C272,C275,C283,C292,C295,C305,C309,C321,C386,C417,C419,C444		1.0uF	CL10B105K08NNNC	Samsung Electro-Mechanics America, Inc	603
33	31	0	C249	DNI	33uF	C4532X7R1C336M250KC	TDK	1812
34	32	0	C253	DNI	22uF	GRM31CR71A226KE15L	MURATA	1206
35	33	2	C311,C394		10uF	GRM21BR61E106KA73L	MURATA	805
36	34	1	C316		47uF	GRM32ER61A476KE20L	MURATA	1210
37	35	1	C317		10uF	C2012X5R0J106M/1.25	TDK	805
38	36	5	C327,C329,C397,C399,C413		5600pF	CLO5B562K05NNNC	Samsung	402
39	37	2	C328,C398		.3pF	GRM1555C1HR30WA01D	MURATA	402
40	38	6	C330,C331,C332,C401,C403,C404		1000pF	CLO5B102K05NNNC	Samsung	402
41	39	17	C342,C343,C344,C345,C346,C347,C348,C349,C350,C351,C352,C353,C356,C357,C358,C374,C377		1uF	CLO5B105K05NQNC	TDK	402
42	40	0	C370	DNI	0.01uF	GRM155R71H103KA88D	MURATA	402
43	41	8	C371,C372,C378,C379,C380,C381,C382,C383		.01uF	GRM033R71A103KA01D	MURATA	201
44	42	2	C391,C392		.047uF	GRM155R71E473KA88J	MURATA	402
45	43	2	C434,C436		47uF	C2012X5R1A476M125AC	TDK	805
46	44	5	D1,D2,D3,D4,D11		LED GREEN	LTST-C150KGKT	LITE ON	LED 1206
47	45	1	D5		LED AMBER	LTST-C150AKT	LITE ON	LED 1206
48	46	3	D8,D9,D10		LED BLUE	LNJ906W5BUX	PANASONIC	LED 0805
49	47	1	FB1		120 OHM @ 100MHZ	BLM31PG121SN1L	MURATA	1206
50	48	10	FB2,FB3,FB4,FB5,FB6,FB7,FB8,FB9,FB10,FB11		120	BLM18AG121SN1D	MURATA	603
51	49	4	FB12,FB14,FB17,FB18		60 OHM @ 100MHZ	FBM3216HM600-T	Taiyo Yuden	1206

1	A	B	C	D	E	F	G	H
2	Item	Quantity	Reference	Note	TIDA-01215 DAC38RF8x EVM Part	Revision: E Part Number	Manufacturer	Foot Print
52	50	21	FB19,FB20,FB21,FB22,FB23,FB24,FB26,FB27,FB28,FB29,FB30,FB31,FB32,FB33,FB34,FB35,FB36,FB37,FB40,FB41,FB42		27uF	NFM31PC276B0J3	Murata	1206_BEAD_NFM31P
53	51	0	F1	DNI	FUSE 2.0A 63V FAST	1206SFF200F/63-2	TE Connectivity	1206
54	52	1	JP1	(SHUNT 2-3)	Jumper 1x3 100 430L	HMTSW-103-07-G-S-230	SAMTEC	HDR_THVT_1x3_100_M
55	53	1	JP2	(SHUNT 1-2)	Jumper 1x3 100 430L	HMTSW-103-07-G-S-230	SAMTEC	HDR_THVT_1x3_100_M
56	54	2	JP3,JP10	SHUNT 1-2	HEADER 1x2 100 430L	HMTSW-102-07-G-S-240	SAMTEC	HDR_THVT_1x2_100_M
57	55	2	JP8,JP9		HEADER 1x2 100 430L	HMTSW-102-07-G-S-240	SAMTEC	HDR_THVT_1x2_100_M
58	56	3	J1,J2,J7		SMA END LAUNCH	142-0711-821	Johnson Components	SMA_SMEL_DUAL_PSF-S01_250x215
59	57	5	J4,J8,J24,J25,J26		SMA THVT_REC	142-0701-201	Johnson Components	SMA_THVT_312x312
60	58	1	J6		SMA END LAUNCH	142-0711-821	Johnson Components	SMA_SMEL_DUAL_PSF-S01_250x215
61	59	1	J11		HMTSW-105-07-G-D-240	HMTSW-105-07-G-D-240	SAMTEC	HDR_THVT_2x5_100_M
62	60	1	J16		USB MINI_AB	678038020	Molex	CON_SMRT_USBMINI_AB_F_mod
63	61	1	J20		CON_SMVIT_40x10_SEAM	SEAM-40-02.0-S-10-2-A-K-TR	SAMTEC	CON_SMVIT_40X10_SEAM_MTG
64	62	1	J21		CONN JACK PWR	RAPC722X	SWITCHCRAFT	CON_RAPC722_JACK_THVT_3
65	63	1	J22	SHUNT 1-2, 3-4, 5-6	HDR 2X3 2mm	57202-G52-03LF	FCI	HDR_SMVIT_2x3_79_M
66	64	1	J23	SHUNT 1-2, 3-4, 5-6, 7-8	HDR 2x4 2mm	57202-G52-04LF	FCI	HDR_SMVIT_2x4_79_M
67	65	0	J27	DNI	SMA END LAUNCH	142-0711-841	Johnson Components	SMA_SMEL_DUAL_PSF-S01_250x215
68	66	0	L1,L2,L7,L8	DNI	560nH	0402AF-561XJLU	Coilcraft	402
69	67	1	L3		1uH	XFL4020-102MEC	Coilcraft	IND_SM_XFL4015
70	68	1	L5		.47uH	XFL4015-471MEB	Coilcraft	IND_SM_XFL4015
71	69	2	L9,L10		560nH	0402AF-561XJLU	Coilcraft	402
72	70	4	MT1,MT2,MT3,MT4	STANDOFF	STANDOFF, 4-40, 3/16 Rd x 1 3/16 Length, ALUM	1648-440-AL	RAF Electronic Hardware	MFG125_PLATED
73	71	20	PP1,PP2,PP3,PP4,PP5,PP7,PP8,PP9,PP10,PP13,PP15,PP17,PP18,PP19,PP20,PP23,PP24,PP25,PP26,PP27		PROBE POINT	N/A	N/A	PROBE_POINT_22PAD
74	72	3	Q1,Q2,Q3		DTC114EET1G	DTC114EET1G	ON Semiconductor	SOT_416_3_63x31
75	73	1	Q4		CSD18532Q5	CSD18532Q5B	TI	SON_Q5B_8
76	74	1	R1		17.8	ERJ-1GEF17R8C	Panasonic	201
77	75	2	R2,R3		294	ERJ-1GEF2940C	Panasonic	201
78	76	0	R4,R5,R29,R48,R243,R280	DNI	49.9	ERJ-1GEF49R9C	PANASONIC	201
79	77	0	R9,R10,R131,R232,R239,R240,R244,R263,R264,R265,R266,R268,R269,R288,R289,R290,R291,R292,R293,R294,R295,R314,R318,R319,R321,R323,R324	DNI	0	ERJ-2GEOR00X	PANASONIC	402
80	78	6	R11,R69,R79,R81,R84,R110		1k	ERJ-2RKF1001X	PANASONIC	402
81	79	1	R12		3.65K	ERJ-2RKF3651X	PANASONIC	402
82	80	0	R20	DNI	24.9K	ERJ-1GEF2492C	PANASONIC	201
83	81	1	R21		39K	ERJ-1GEF3902C	PANASONIC	201
84	82	8	R22,R23,R31,R36,R55,R57,R103,R104		0	ERJ-1GNOR00C	PANASONIC	201
85	83	0	R24,R25,R26,R27,R41,R42,R45,R46,R50,R51,R56,R	DNI	240	ERJ-1GEF2400C	PANASONIC	201
86	84	1	R28		620	ERJ-1GEF6200C	PANASONIC	201
87	85	0	R30	DNI	0	ERJ-3GEYOR00V	PANASONIC	603
88	86	1	R32		18	ERJ-2RKF18R0X	PANASONIC	402
89	87	2	R33,R34		292	ERJ-2RKF2940X	PANASONIC	402
90	88	1	R35		49.9	ERJ-2RKF49R9X	PANASONIC	402
91	89	2	R37,R38		240	ERJ-1GEF2400C	PANASONIC	201
92	90	5	R39,R40,R52,R106,R107		100	ERJ-1GEF1000C	PANASONIC	201
93	91	0	R43,R49	DNI	130	ERJ-1GEF1300C	Panasonic	201
94	92	0	R44,R267	DNI	100	ERJ-1GEF1000C	PANASONIC	201
95	93	0	R47,R53	DNI	82	ERJ-1GEF82R0C	Panasonic	201
96	94	6	R54,R218,R219,R283,R287,R329		49.9	ERJ-1GEF49R9C	PANASONIC	201
97	95	4	R59,R60,R61,R62		750	CRCW0603750RFKEA	DALE	603
98	96	1	R63		3.01K	ERJ-2RKF3011X	PANASONIC	402
99	97	2	R64,R250		0	ERJ-3GEYOR00V	PANASONIC	603
100	98	2	R65,R66		10	ERJ-2RKF10R0X	PANASONIC	402
101	99	1	R67		4.7K	ERJ-2RKF4701X	PANASONIC	402
102	100	1	R68		12K	ERJ-2RKF1202X	PANASONIC	402
103	101	6	R70,R71,R72,R73,R224,R252		10K	ERJ-2RKF1002X	PANASONIC	402
104	102	1	R74		2.2K	RC0402FR-072K2L	Yageo	402
105	103	18	R80,R82,R83,R129,R130,R140,R148,R179,R180,R181,R182,R183,R184,R185,R186,R286,R317,R320		0	ERJ-2GEOR00X	Panasonic	402
106	104	1	R115		1.13k	ERJ-2RKF1131X	Panasonic	402
107	105	1	R116		4.53k	ERJ-2RKF4531X	Panasonic	402
108	106	3	R121,R122,R297		0	5108	KEYSTONE	1206
109	107	1	R125		255k	ERJ-2RKF2553X	PANASONIC	402

	A	B	C	D	E	F	G	H
1					TIDA-01215 DAC38RF8x EVM	Revision: E		
2	Item	Quantity	Reference	Note	Part	Part Number	Manufacturer	Foot Print
110	108	2	R126,R226		499k	ERJ-2RKF4993X	PANASONIC	402
111	109	6	R173,R174,R175,R176,R177,R178		22	ERJ-2RKF22R0X	PANASONIC	402
112	110	1	R187		1.3K	ERJ-2RKF1301X	Panasonic	402
113	111	0	R199,R229	DNI	100	ERJ-2GEOR00X	PANASONIC	402
114	112	2	R210,R211		11.3	ERJ-2RKF11R3X	Panasonic	402
115	113	1	R212		71.5	ERJ-2RKF71R5X	Panasonic	402
116	114	3	R213,R214,R215		0.18	ERJ-2B5FR18X	Panasonic	402
117	115	0	R221	DNI	102k	ERJ-2RKF1023X	PANASONIC	402
118	116	2	R222,R228		162k	ERJ-2RKF1623X	Panasonic	402
119	117	1	R225		12.7k	ERJ-2RKF1272X	Panasonic	402
120	118	0	R227	DNI	348k	ERJ-2RKF3483X	PANASONIC	402
121	119	0	R233	DNI	22	ERJ-2RKF22R0X	PANASONIC	402
122	120	0	R238,R241,R248,R249	DNI	0	ERJ-3GEY0R00V	PANASONIC	603
123	121	0	R242	DNI	49.9	ERJ-2RKF49R9X	PANASONIC	402
124	122	0	R254	DNI	1.27K	ERJ-2RKF1271X	PANASONIC	402
125	123	3	R255,R258,R285		100k	ERJ-2RKF1003X	PANASONIC	402
126	124	0	R256	DNI	10K	ERJ-2RKF1002X	PANASONIC	402
127	125	3	R272,R273,R274		0	ERJ-2GEOR00X	PANASONIC	402
128	126	1	R282		97.6	ERJ-2RKF97R6X	PANASONIC	402
129	127	0	R284,R296	DNI	0	5108	KEYSTONE	1206
130	128	1	R298		40.2k	ERJ-2RKF4022X	PANASONIC	402
131	129	17	R299,R300,R301,R302,R303,R304,R305,R306,R307,R308,R309,R310,R311,R312,R315,R316,R332		0	5106	KEYSTONE	805
132	130	1	R330		205k	ERJ-2RKF2053X	PANASONIC	402
133	131	0	R331,R333	DNI	0	5106	KEYSTONE	805
134	132	4	SHN1,SHN2,SHN17,SHN18		SHUNT HEADER	MJ-5.97-G or equivalent	Keltron	
135	133	7	SHN5,SHN6,SHN7,SHN8,SHN9,SHN10,SHN11		SHUNT, JUMPER 2mm	NPNO25XLN-RC	Sullins	
136	134	0	SJP1	DNI	SOLDER JUMPER, 0402	DNI	DNI	SMD JUMPER L 0402
137	135	1	SW1		DAC RESET	PTS6355L43 LFS	C&K Components	sw_thvt_sps_tps6355l43
138	136	3	TP1,TP2,TP14		BLK	5001	KEYSTONE	TP_THVT_060_RND
139	137	2	TP9,TP10		YELLOW	5004	KEYSTONE	TP_THVT_060_RND
140	138	1	TP21		Testloop_Red	5010	Keystone	testpoint_62dia
141	139	1	TP22		Testloop_Black	5011	KEYSTONE	testpoint_62dia
142	140	1	T1		NCR2-113+	NCR2-113+	MINI-CIRCUITS	BALUN 6 NCR2
143	141	1	T3		TC1-1-13M+	TC1-1-13M+	Mini-Circuits	TFMR 5_150x150_50
144	142	2	T5,T7		TCM3-452X-1+	TCM3-452X-1+	Mini-Circuits	TFMR 6_160x150_50
145	143	1	T8		TCM2-43X+	TCM2-43X+	Mini-Circuits	TFMR 6_160x150_50
146	144	1	U1		DAC38RF83	DAC38RF83IAAV	Texas Instruments	BGA_144_10MMx10MM_OP80MM
147	145	1	U2		LMK04828	LMK04828BISQ	Texas Instruments	QFN_64_360x360_OP50MM_PWRPAD
148	146	1	U4		FT2232H	FT2232H	FTDI	LQFP_64_402x402_20
149	147	1	U5		93LC46B-I/MS	93LC46B-I/MS	Microchip	MSOP_8_118x118_26
150	148	1	U9		TPS2400	TPS2400DBVT	Texas Instruments	DBV5
151	149	1	U12		TPS74401/QFN20	TPS74401RSGWT	Texas Instruments	qfn_20_197x197_0p65_rgw
152	150	1	U19		LM27761	LM27761DSGR	Texas Instruments	SON_DSG_8
153	151	1	U21		TPS7A4700	TPS7A4700RSGWT	Texas Instruments	qfn20_rgw_p65pitch
154	152	1	U23		LP5907-3.3	LP5907MPX-3.3/NOPB	Texas Instruments	DBV5
155	153	1	U29		TXS0108E	TXS0108ERGVY	Texas Instruments	QFN_20_183x144_RGY
156	154	1	U30		NB7V33M	NB7V33M	On Semi	qfn_16_124x124_pwrpad
157	155	1	U31		TPS62095	TPS62095RGT	Texas Instruments	QFN_16_124x124_RGT
158	156	1	U34		TPS7A8101	TPS7A8101DRB	Texas Instruments	SON_DRB_8
159	157	1	U35		TPS62085	TPS62085RLTR	Texas Instruments	QFN_RLT_7
160	158	1	U37		TPS7A8500	TPS7A8500RGR	Texas Instruments	QFN20_RGR_p5mm
161	159	1	Y1		122.88MHz	CVHD-950-122.880	Crystek	VXCO_6_CUSTOM
162	160	1	Y2		12MHz w/ 10pF	ABM8G-12.000MHZ-B4Y-T	Abracon	XTAL_4_SM_130X102
163	161	4	Z_SCREW1,Z_SCREW2,Z_SCREW3,Z_SCREW4	OR EQUIVALENT	SCREW, PHIL, 4-40x3/8", SS	PMSSS 440 0038 PH	BUILDING FASTENERS	
164	162	1			HEATSINK, EXTRUDED, RED	10-1003850	SVT	

IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Designer(s)") who are developing systems that incorporate TI products. TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.

TI's provision of reference designs and any other technical, applications or design advice, quality characterization, reliability data or other information or services does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such reference designs or other items.

TI reserves the right to make corrections, enhancements, improvements and other changes to its reference designs and other items.

Designer understands and agrees that Designer remains responsible for using its independent analysis, evaluation and judgment in designing Designer's systems and products, and has full and exclusive responsibility to assure the safety of its products and compliance of its products (and of all TI products used in or for such Designer's products) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to its applications, it has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any systems that include TI products, Designer will thoroughly test such systems and the functionality of such TI products as used in such systems. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

Designers are authorized to use, copy and modify any individual TI reference design only in connection with the development of end products that include the TI product(s) identified in that reference design. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of the reference design or other items described above may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS AND OTHER ITEMS DESCRIBED ABOVE ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNERS AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS AS DESCRIBED IN A TI REFERENCE DESIGN OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

TI's standard terms of sale for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>) apply to the sale of packaged integrated circuit products. Additional terms may apply to the use or sale of other types of TI products and services.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2016, Texas Instruments Incorporated