

TIDA-01373 REV E1 Bill of Materials

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
3v3, 3v3-ISO, 5v, 5v-ISO, 5v-Other-Reg, 5v-USB-Reg, 5v_pre, Back, Contrast, D0.1, D0.2, D1.1, D1.2, D2.1, D2.2, D3.1, D3.2, D4.1, D4.2, D5.1, D5.2, D6.1, D6.2, D7.1, D7.2, Done, E.1, E.2, GND1, Next, Program, R/W.1, R/W.2, Read, Reset, RS.1, RS.2, SCL, SCL0-ISO, SCL1-ISO, SCL2-ISO, SCL3-ISO, SCL4-ISO, SCL5-ISO, SCL6-ISO, SCL7-ISO, SCL-ISO, SDA, SDA0-ISO, SDA1-ISO, SDA2-ISO, SDA3-ISO, SDA4-ISO, SDA5-ISO, SDA6-ISO, SDA7-ISO, SDA-ISO, Test, USB_Vin, Vin	60		5016	Keystone	Test Point, Compact, SMT	Testpoint_Keystone_Compact
Back_button, Done_button, Next_button, Program_button, Read_button, Reset_button	6		430182070816	Würth Elektronik	Switch, SPST-NO, Off-Mom, 1 Pos, 0.05A, 12 VDC, SMT	6.2x6.2mm
C0, C5, C6, C8, C9, C10, C27	7	0.1uF	C0603C104K8RACTU	Kemet	CAP, CERM, 0.1 µF, 10 V, +/- 10%, X7R, 0603	0603
C1	1	22uF	GRM32ER61E226KE15L	MuRata	CAP, CERM, 22 µF, 25 V, +/- 10%, X5R, 1210	1210
C2	1	0.1uF	GRM155R61C104KA88D	MuRata	CAP, CERM, 0.1 µF, 16 V, +/- 10%, X5R, 0402	0402
C3	1	10uF	GRM188R61C106MAALD	MuRata	CAP, CERM, 10 µF, 16 V, +/- 20%, X5R, 0603	0603
C4	1	47uF	GRM31CR61A476KE15L	MuRata	CAP, CERM, 47 µF, 10 V, +/- 10%, X5R, 1206	1206
C11, C14, C16, C18, C21	5	4.7uF	GRM219R60J475KE19D	MuRata	CAP, CERM, 4.7 µF, 6.3 V, +/- 10%, X5R, 0805	0805
C12, C13, C15, C17, C20	5	0.1uF	GRM155R71A104KA01D	MuRata	CAP, CERM, 0.1 µF, 10 V, +/- 10%, X7R, 0402	0402
C22, C23	2	12pF	C0402C120J3GACAUTO	Kemet	CAP, CERM, 12 pF, 25 V, +/- 5%, C0G/NP0, AEC-Q200 Grade 1, 0402	0402
C24	1	4.7uF	GRM219C80J475KE19D	MuRata	CAP, CERM, 4.7 µF, 6.3 V, +/- 10%, X6S, 0805	0805

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
C25	1	0.1uF	C0805C104K4RACTU	Kemet	CAP, CERM, 0.1 µF, 16 V, +/- 10%, X7R, 0805	0805
C26	1	22uF	C5750X7R1E226M250KA	TDK	CAP, CERM, 22 µF, 25 V, +/- 20%, X7R, 2220	2220
F1, F2, F3	3		0263001.WRT1L	Littelfuse	Fuse, 1 A, 250VAC/VDC, TH	Fuse, 7.11x3.94mm
FID1, FID2, FID3	3		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	Fiducial
H1, H2, H3, H4	4		NY PMS 440 0025 PH	B&F Fastener Supply	Machine Screw, Round, #4-40 x 1/4, Nylon, Philips panhead	Screw
H5, H6, H7, H8	4		1902C	Keystone	Standoff, Hex, 0.5"L #4-40 Nylon	Standoff
IC1	1		MSP430G2553IRHB32R	Texas Instruments	16 MHz Mixed Signal Microcontroller with 16 KB Flash, 512 B SRAM and 24 GPIOs, -40 to 85 degC, 32-pin QFN (RHB), Green (RoHS & no Sb/Br)	RHB0032E
J3	1		30320-6002HB	3M	Straight Low Profile Header, 10x2 Position, 2.54 mm Pitch, TH	Male Header, 10x2 Position, 2.54 mm Pitch, Straight, TH
J4, JTAG	2		SBH11-PBPC-D07-ST-BK	Sullins Connector Solutions	Header (shrouded), 100 mil, 7x2, Gold, TH	7x2 Shrouded Header
J5	1		1734035-2	TE Connectivity	Connector, Receptacle, Mini-USB Type B, R/A, Top Mount SMT	USB Mini Type B
J6	1		1715721	Phoenix Contact	Terminal Block, 5.08 mm, 2x1, TH	2POS Terminal Block
J7	1		PJ-002BH-SMT-TR	CUI Inc.	Power Jack, 2.5x5.5mm, R/A, SMT	Power Jack, 4-Leads, Body 14.8x9mm, R/A, SMT
J8, J9, J10, J11	4		D3082-05	Harwin	1mm Uninsulated Shorting Plug, 10.16mm spacing, TH	Shorting Plug, 10.16mm spacing, TH
L1	1	1.5uH	XFL4020-152MEB	Coilcraft	Inductor, Shielded, Composite, 1.5 µH, 4.6 A, 0.01 ohm, SMD	4x2x4mm
L2	1	1000 ohm	BK2125HS102-T	Taiyo Yuden	Ferrite Bead, 1000 ohm @ 100MHz, 0.3A, 0805	0805
PWRLED	1	Green	QTLP630C4TR	Everlight	LED, Green, SMD	2x1.25mm
R1	1	10.0k	CRCW040210K0FKED	Vishay-Dale	RES, 10.0 k, 1%, 0.063 W, 0402	0402
R3	1	47.5k	ERJ-3EKF4752V	Panasonic	RES, 47.5 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0603	0603
R4, R5, R7, R8, R9	5	47.0k	RT0603BRD0747KL	Yageo America	RES, 47.0 k, 0.1%, 0.1 W, 0603	0603
R10, R11	2	4.70k	RG1608P-472-B-T5	Susumu Co Ltd	RES, 4.70 k, 0.1%, 0.1 W, 0603	0603
R12, R13, R14, R15, R16, R17, R18, R19, R20, R21, R22, R23, R24, R25, R26, R27, R28, R29, R32	19	4.70k	RC1206FR-074K7L	Yageo America	RES, 4.70 k, 1%, 0.25 W, 1206	1206
R30, R31	2	10.0	ERJ-8ENF10R0V	Panasonic	RES, 10.0, 1%, 0.25 W, 1206	1206
R33	1	270	RG1608P-271-B-T5	Susumu Co Ltd	RES, 270, 0.1%, 0.1 W, 0603	0603
R35	1	100k	CRCW0603100KFKEA	Vishay-Dale	RES, 100 k, 1%, 0.1 W, 0603	0603
R36	1	25k ohm	296XD253B1N	CTS Electrocomponents	Trimmer, 25k ohm, 0.15W, TH	6.3x12.5mm
S1on/off	1		B12AP	NKK Switches	SWITCH TOGGLE SPDT 0.4VA 28V	6.8x23.1x8.8mm
S2_usb/other	1		25139NAH	APEM	Switch, SPDT, On-Off-On, 1 A, 30 VDC, TH	14.1x7.5mm
TVS1	1	10V	SMAJ10A	Littelfuse	Diode, TVS, Uni, 10 V, SMA	SMA
U1	1		TPS630701RNMR	Texas Instruments	2-V to 16-V Buck-Boost Converter With 3.6-A Switch Current, RNM0015A (VQFN-HR-15)	RNM0015A
U2, U5	2		LP5907MFX-3.3/NOPB	Texas Instruments	ULTRA LOW-NOISE, 250-mA LINEAR REGULATOR FOR RF AND ANALOG CIRCUITS REQUIRES NO BYPASS CAPACITOR, DBV0005A	DBV0005A
U3, U7, U8	3		TPD8E003DQDR	Texas Instruments	ESD Array For Portable Space-Saving Applications, 8 Channels, -40 to +85 degC, 8-pin WSON (DQD), Green (RoHS & no Sb/Br)	DQD0008A
U4	1		DCP010505BP-U	Texas Instruments	Miniature, 1 W Isolated Unregulated DC-DC Converter, -40 to 100 degC, 7-pin SOP (DUA7), Pb-Free (RoHS)	DUA0007A

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
U6	1		ISO1541DR	Texas Instruments	Low-Power Bidirectional I2C Isolators, D0008A	D0008A
U9	1		TCA9548APW	Texas Instruments	LOW VOLTAGE 8-CHANNEL I2C SWITCH WITH RESET, PW0024A	PW0024A
U10	1		TPD3S014DBVR	Texas Instruments	Integrated USB Protection with VBUS Current Limit, DBV0006A	DBV0006A
U11	1		EA DIPS082-HNLED	Electronic Assembly	LCD-Modul with Led Backlight Yellow/Green, 2X8, TH	LCD Module, 40x20mm
U12, U13, U14	3		SN74LV4T125PWR	Texas Instruments	Single Power Supply Quadruple Buffer Translator GATE With 3-State Output CMOS Logic Level Shifter, PW0014A	PW0014A
Y1	1		FC-135 32.7680KA-A3	Epson	Crystal, 32.768 KHz, 12.5 pF, SMD	SMD, 2-Leads, Body 3.2x1.5mm

IMPORTANT NOTICE FOR TI DESIGN INFORMATION AND RESOURCES

Texas Instruments Incorporated ("TI") technical, application or other design advice, services or information, including, but not limited to, reference designs and materials relating to evaluation modules, (collectively, "TI Resources") are intended to assist designers who are developing applications that incorporate TI products; by downloading, accessing or using any particular TI Resource in any way, you (individually or, if you are acting on behalf of a company, your company) agree to use it solely for this purpose and subject to the terms of this Notice.

TI's provision of TI Resources does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such TI Resources. TI reserves the right to make corrections, enhancements, improvements and other changes to its TI Resources.

You understand and agree that you remain responsible for using your independent analysis, evaluation and judgment in designing your applications and that you have full and exclusive responsibility to assure the safety of your applications and compliance of your applications (and of all TI products used in or for your applications) with all applicable regulations, laws and other applicable requirements. You represent that, with respect to your applications, you have all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. You agree that prior to using or distributing any applications that include TI products, you will thoroughly test such applications and the functionality of such TI products as used in such applications. TI has not conducted any testing other than that specifically described in the published documentation for a particular TI Resource.

You are authorized to use, copy and modify any individual TI Resource only in connection with the development of applications that include the TI product(s) identified in such TI Resource. NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information regarding or referencing third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of TI Resources may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI RESOURCES ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING TI RESOURCES OR USE THEREOF, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY YOU AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS EVEN IF DESCRIBED IN TI RESOURCES OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF TI RESOURCES OR USE THEREOF, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

You agree to fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of your non-compliance with the terms and provisions of this Notice.

This Notice applies to TI Resources. Additional terms apply to the use and purchase of certain types of materials, TI products and services. These include; without limitation, TI's standard terms for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>), [evaluation modules](#), and [samples](http://www.ti.com/sc/docs/sampterm.htm) (<http://www.ti.com/sc/docs/sampterm.htm>).

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2017, Texas Instruments Incorporated