

# Bill of Materials

2516741  
DLPC3434 System Board

Item	Qty	Reference	Value	Part Description	Manufacturer	Manufacturer Part Number	Alternate Part	PCB Footprint	Note
1	3	C1,C2,C3	47uF	CAP CER 47UF 10V X5R 1206	Taiyo Yuden	LMK316BJ476ML-T		1206	
2	2	C4,C5	100uF	CAP ALUM 100UF 25V 20% SMD	Panasonic	EEE-FT1E101AP		sizeD_260x260mil_radial_can	
3	6	C6,C10,C15,C16,C17,C18	10uF	CAP CER 10UF 35V 10% X5R 1206 SMD	Taiyo Yuden	GMK316BJ106KL-T		1206	
4	30	C7,C14,C27,C35,C37,C41, C42,C52,C53,C56,C57,C58, C59,C60,C61,C62,C63,C64, C68,C69,C70,C71,C72,C73, C74,C75,C76,C77,C86,C88	0.1uF	0.10uF 50V Ceramic Capacitor X7R 0402	TDK	CGA2B3X7R1H104K050BB		402	
5	1	C8	3300pF	CAP CER 3300PF 50V 10% X7R 0805	Samsung	CL21B332KBANNNC		805	
6	1	C9	56pF	56pF 50V Ceramic Capacitor COG, NP0 0805	Yageo	CC0805JRNPO9BN560		805	
7	1	C11	100uF	CAP CER 100UF 6.3V X5R 1206	Samsung	CL31A107M0HNNNE		1206	
8	1	C12	680pF	680pF 50V Ceramic Capacitor X7R 0805	Yageo	CC0805KRX7R9BB881		805	
9	1	C13	39.0nF	0.039uF 10V Ceramic Capacitor X5R 0402	Murata	GRM155R61A393KAO1D		402	
10	1	C19	22pF	CAP CER 22PF 50V 5% NP0 0402	Murata	GRM1555C1H220JAO1D		402	
11	2	C20,C31	4.7uF	CAP CER 4.7UF 6.3V 20% X5R 0402	TDK	C1005X5R0J475M050BC		402	
12	8	C21,C22,C23,C24,C26,C28, C32,C65	2.2uF	2.2uF 25V Ceramic Capacitor X5R 0603	Taiyo Yuden	TMK107ABJ225KA-T		603	
13	3	C25,C33,C39	10uF	CAP CERAMIC 10UF 6.3V X5R 0603	TDK	C1608X5R0J106M080AB		603	
14	1	C29	30pF	CAP CER 30PF 50V 5% NP0 0402	Murata	GRM1555C1H300JAO1D		402	
15	1	C30	27pF	CAP CER 27PF 50V 5% NP0 0402	Murata	GRM1555C1H270JAO1D		402	
16	1	C34	10nF	10000pF 25V Ceramic Capacitor X7R 0402	Murata	GRM155R71E103KAO1D		402	
17	1	C36	1uF	CAP CER 1.0UF 10V X5R 0402	Murata	GRM153R61A105ME95D		402	
18	25	C38,C43,C44,C45,C46,C47, C48,C50,C51,C55,C66,C67, C80,C81,C82,C83,C84,C85, C87,C90,C91,C92,C93,C94, C95	0.1uF	CAP CER .1UF 16V X7R 0402	TDK	C1005X7R1C104K050BC		0402 AVXA	
19	0	C40,C89	0.1uF	CAP CER .1UF 16V X7R 0402	TDK	C1005X7R1C104K050BC		0402 AVXA	
20	1	C49	0.47uF	CAP CER 0.47UF 35V 10% X5R 0402	Taiyo Yuden	UMK105ABJ474KV-F		402	
21	1	C54	0.22uF	CAP CER .22UF 6.3V X7R 10% 0402	Taiyo Yuden	JMK105B7224KV-F		402	
22	2	C78,C79	18pF	CAP CER 18PF 50V NP0 5% 0402	Murata	GRM1555C1H180JAO1D		402	
23	1	DN1	BAT54C	DIODE ARRAY SCHOTTKY 30V 200mA SOT23-3	Diodes Inc.	BAT54C-7-F		SOT-23-3	
24	8	D1,D3,D4,D5,D6,D7,D9,D10	blue	LED INGAN/SiC U-BLUE CLR 1206SMD	Lumex	SML-LX1206UBC-TR		1206	
25	1	D2	SMAJ22A	TVS DIODE 22VWWM SMD package DO214AC SMA	Bourns	SMAJ22A		SMA	
26	1	D8	green	LED 565NM WTR CLR GREEN 1206 SMD	Lumex	SML-LX1206GC-TR		1206	
27	5	FB1,FB2,FB3,FB4,FB5	BKP1005EM121-T	FERRITE CHIP 80 OHM 1500MA 0402	Taiyo Yuden	BKP1005EM121-T		402	
28	1	F1	5A	FUSE BRD MNT 5A 32VAC 35VDC 1206	Littlefuse	0437005.WR		1206	
29	1	J1	SBH11-PBPC-D07-RA-BK	CONN HEADER 2.54MM 14POS GOLD R/A	Sullins	SBH11-PBPC-D07-RA-BK		SBH11-D07-RA	
30	0	J2	B5B-ZR	CONN HEADER ZH TOP 5POS 1.5MM	JST	B5B-ZR-SM4-TF(LF)(SN)		JST B5B-ZR-SM4-TF LF SN P	
31	0	J3	B4B-ZR	CONN HEADER ZH TOP 4POS 1.5MM	JST	B4B-ZR-SM4-TF(LF)(SN)		JST B4B-ZR-SM4-TF LF SN P	
32	1	J4	PJ-082BH	CONN PWR JACK 2.5X5.5MM SOLDER	CUI Inc	PJ-082BH		CUI PJ-082BH	
33	0	J5	B6B-ZR	CONN HEADER ZH TOP 6POS 1.5MM	JST	B6B-ZR-SM4-TF(LF)(SN)		JST B6B-ZR-SM4-TF LF SN P	
34	1	J6	M20-9990245	CONN HEADER 2 POS 0.1IN SIL VERT	Hanwin	M20-9990245		HDR2P 1R	
35	3	J7,J8,J9	S2B-ZR	CONN HEADER ZH SIDE 2POS 1.5MM	JST	S2B-ZR(LF)(SN)		JST S2B_ZR	
36	1	J10	QSH-030-01-L-D-A	CONN RCPT HI-SPD .5MM 60POS DL (stacking ht 5mm)	Samtec	QSH-030-01-L-D-A		Samtec_QSH-030-xxx-D-A	
37	1	J11	HDMI Type C (Mini) Receptacle	MINI HDMI 19P FEMALE SMT	CNC Tech	2001-1-2-21-00-BK		CNC-2001-1-2-21-00-BK	
38	1	J12	USB - Mini-B USB 2.0	CONN RECEPT MINI-USB R/A 5POS SMD	Molex	0513870578		MOLEX_USB_CONN_0513870578	
39	0	J13	S4B-EH(LF)(SN)	CONN HEADER EH SIDE 4POS 2.5MM	JST	S4B-EH(LF)(SN)		CONN4-S4B-EH_JST	
40	1	L1	10uH	Inductor 10 uH 6 A 20% SMD	Coilcraft	XAL8080-103MEB		Coilcraft_XAL8080	
41	1	L2	10uH	FIXED IND 10UH 3.8A 25 MOHM SMD	Bourns	SRU1038-100Y		Bourns SRU1038	
42	1	L3	2.2uH	INDUCTOR 2.2UH 20% 1300MA 1008	Murata	LQM2HPN2R2MGOL		1008_2p5mmx2mm	
43	1	Q1	DMN26D0UT-7	MOSFET N-CH 20V 230MA SOT523	Diodes	DMN26D0UT-7		SOT_523	
44	6	RP1,RP2,RP3,RP4,RP5,RP6	22	RES ARRAY 4 RES 22 OHM 0804	Panasonic	EXB-N8V220JX		804	
45	2	R1,R8	0	RES SMD 0.0 OHM JUMPER 1/8W 0805	Panasonic	ERJ-6GEY0R00V		805	
46	1	R2	150	RES 150 OHM 1/10W 1% 0402 SMD	Panasonic	ERJ-2RKF1500X		402	
47	1	R3	10.7k	RES SMD 10.7K OHM 1% 1/16W 0402	Vishay Dale	CRCW040210K7FKED		402	
48	15	R4,R33,R36,R42,R50,R52, R53,R59,R60,R61,R77,R87, R88,R91,R93	0	RES 0.0 OHM 1/16W 0402 SMD	Panasonic	ERJ-2GEOR00X		402	
49	4	R5,R9,R71,R76	100k	RES SMD 100K OHM 1% 1/16W 0402	Vishay Dale	CRCW0402100KFED		402	
50	1	R6	19.1k	RES SMD 19.1K OHM 1% 1/8W 0805	Panasonic	ERJ-6ENF1912V		805	
51	7	R7,R18,R19,R20,R24,R82, R89	10	RES 10.0 OHM 1/10W 1% 0402 SMD	Panasonic	ERJ-2RKF10R0X		402	
52	1	R10	32.4k	RES SMD 32.4K OHM 1% 1/8W 0805	Panasonic	ERJ-6ENF3242V		805	
53	1	R11	2.15k	RES SMD 2.15K OHM 1% 1/16W 0402	Vishay Dale	CRCW040221K5FKED		402	
54	2	R12,R15	274k	RES SMD 274K OHM 1% 1/16W 0402	Vishay Dale	CRCW0402274KFKED		402	
55	2	R13,R16	30.9k	RES SMD 30.9K OHM 1% 1/16W 0402	Vishay Dale	CRCW040230K9FKED		402	
56	1	R14	95.3k	RES SMD 95.3K OHM 1% 1/16W 0402	Vishay Dale	CRCW040295K3FKED		402	
57	1	R17	97.6k	RES SMD 97.6K OHM 1% 1/16W 0402	Vishay Dale	CRCW040297K6FKED		402	
58	12	R21,R22,R23,R31,R32,R47, R48,R49,R54,R67,R68,R69 R25,R27,R30,R35,R57,R70, R72,R73,R78,R80,R81,R83, R85,R90,R95,R96,R97,R98,	30.1	RES 30.1 OHM 1/16W 1% 0402 SMD	Panasonic	ERJ-2RKF30R1X		402	
59	25	R99,R101,R102,R103,R106, R107,R109	10k	RES SMD 10K OHM 1% 1/10W 0402	Panasonic	ERJ-2RKF1002X		402	
60	2	R26,R92	47k	RES 47.0K OHM 1/10W 1% 0402 SMD	Panasonic	ERJ-2RKF4702X		402	
61	2	R28,R29	180k	RES 180K OHM 1/16W 1% 0402 SMD	Yageo	RC0402FR-07180KL		402	
62	0	R34,R41,R51,R58,R79,R86, R94,R108	0	RES 0.0 OHM 1/16W 0402 SMD	Panasonic	ERJ-2GEOR00X		402	
63	12	R37,R39,R40,R43,R44,R45, R46,R62,R63,R64,R65,R66	22	RES SMD 22 OHM 1% 1/10W 0402	Panasonic	ERJ-2RKF22R0X		402	

Item	Qty	Reference	Value	Part Description	Manufacturer	Manufacturer Part Number	Alternate Part	PCB Footprint	Note
64	1	R38	3.16k	RES SMD 3.16K OHM 1% 1/10W 0603	Panasonic	ERJ-3EKF3161V		603	
65	1	R55	30.1k	RES SMD 30.1K OHM 1% 1/10W 0402	Panasonic	ERJ-2RKF3012X		402	
66	1	R56	14.3k	RES SMD 14.3K OHM 1% 1/10W 0402	Panasonic	ERJ-2RKF1432X		402	
67	1	R74	100	RES 100 OHM 1/10W 1% 0402 SMD	Panasonic	ERJ-2RKF1000X		402	
68	1	R75	1k	RES SMD 1K OHM 1% 1/16W 0402	Yageo	RC0402FR-071KL		402	
69	0	R84	10k	RES SMD 10K OHM 1% 1/10W 0402	Panasonic	ERJ-2RKF1002X		402	
70	1	R100	1.5k	RES 1.50K OHM 1/10W 1% 0402 SMD	Panasonic	ERJ-2RKF1501X		402	
71	2	R104,R105	1M	RES 1M OHM 1/10W 1% 0402 SMD	Panasonic	ERJ-2RKF1004X		402	
72	1	SW1	TL1105F100Q	SWITCH TACTILE SPST-NO 0.05A 12V TH	Eswitch	TL1105F100Q		TL1105F100Q	
73	1	SW2	GT11MSCBE	SWITCH TOGGLE SPDT ULTRAMINI SMD	C&K	GT11MSCBE		GT11MSCBE	
74	8	TPGND1,TPGND2,TPGND3,TPGND4,TPGND5,TPGND6,TPGND7,TPGND8	TP_BLK	TEST POINT PC MINI .040inD BLACK	Keystone	5001		KEYSTONE_TP_MINIATURE	
75	1	U1,U2	TPS54335ADDA	IC REG BCK ADJ 3A SYNC 8SOPWRPAD	Texas Instruments	TPS54335ADDAR		8-SO-PWRPAD_DDA_R-PDSO-G8	
76	4	U3,U4,U6,U22	SN74AUP1G06DCK	IC INVERTER SINGLE 1INPUT SC705, open drain	Texas Instruments	SN74AUP1G06DCKR		U_5_DCK	
77	3	U5,U9,U12	SN74AVC4T774PWR	IC BUS TRANSCVR 4BIT DL 16TSSOP	Texas Instruments	SN74AVC4T774PWR		TSSOP16_PW	
78	4	U7,U16,U23,U30	SN74AUP1G07DCK	IC BUFF/DVR LOW PWR N-INV SC705, open drain	Texas Instruments	SN74AUP1G07DCKR		U_5_DCK	
79	1	U8	TPS62260DDCT	IC REG BUCK SYNC ADJ TSOT23-5	Texas Instruments	TPS62260DDCT		TSOT-23_DDC_R-PDSO-G5	
80	2	U10,U31	SN74AUP1T17DCK	IC BUFFER SCHMITT TRIG LP SC70-5	Texas Instruments	SN74AUP1T17DCKR		SC70_5_DCK	
81	1	U11	M24C02-WMN	IC EEPROM 2KBIT 400KHZ 8SO	STMicro	M24C02-WMN6TP		SO8	
82	1	U13	MSP430F5529IPN	IC MCU 16BIT 128KB FLASH 80LQFP	Texas Instruments	MSP430F5529IPN		80-LQFP_PN_S-PQFP-G80	
83	1	U14	ITE6801FN	IC RCVR HDMI SINGLE PORT 76-QFN	ITE	ITE6801FN		ITE6801_76pin_QFN	
84	1	U15	TPS73001DBV	IC REG LDO ADJ 0.2A SOT23-5	Texas Instruments	TPS73001DBVR		SOT23-5_DBV_R-PDSO-G6	
85	3	U17,U18,U20	TXS0102	IC VOLT-LEVEL TRANSLATOR 8-US8	Texas Instruments	TXS0102DCUR		VSSOP-8_DCU	
86	1	U19	TPS2061CDBVT	IC PWR DIST SWITCH SGL SOT23-5	Texas Instruments	TPS2061CDBVT		SOT-763	
87	1	U21	CY7C65215-32LTXI	IC USB TO UART BRIDGE DUAL 32QFN	Cypress	CY7C65215-32LTXI		CY7C65215_32pin_QFN	
88	3	U24,U25,U29	TPD2E001DRYR	IC ESD-PROT ARRAY 2CH 6-SON	Texas Instruments	TPD2E001DRYR		U_6_DRY	
89	2	U26,U27	TPD4E05U06DQAR	TVS DIODE 5.5VWM 14VC 10SON	Texas Instruments	TPD4E05U06DQAR		10-UFDFN	
90	1	U28	TPD2E2U06DRL	TVS DIODE 5.5VWM 12.4VC 5SOT	Texas Instruments	TPD2E2U06DRLR		SOT-5_DRL_R-PDSO-N5	
91	1	X1	27MHz	CRYSTAL 27MHZ 18P ±30ppm 60 Ohm 4P CSMD	CTS	403C35D27M00000		4SMD	
92	1	PCB	N/A	PCB, DLPC3434 SYSTEM BOARD REFERENCE DESIGN	Any	DLPC3434_SYSTEM_BOARD		N/A	

## IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale ([www.ti.com/legal/termsofsale.html](http://www.ti.com/legal/termsofsale.html)) or other applicable terms available either on [ti.com](http://ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2019, Texas Instruments Incorporated