

TIDA-01358 REV A Bill of Materials

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	PCB	1		TIDA-01358	Any	Printed Circuit Board	
2	C1	1	3.3uF	C1608X5R1E335K080AC	TDK	CAP, CERM, 3.3 µF, 25 V, +/- 10%, X5R, 0603	0603
3	C2	1	0.22uF	C1005X5R1E224M050BC	TDK	CAP, CERM, 0.22 µF, 25 V, +/- 20%, X5R, 0402	0402
4	C3	1	3.3uF	C3225X7S2A335M200AB	TDK	CAP, CERM, 3.3 µF, 100 V, +/- 20%, X7S, 1210	1210
5	C4	1	47pF	GRM1555C1H470FA01D	MuRata	CAP, CERM, 47 pF, 50 V, +/- 1%, C0G/NP0, 0402	0402
6	C6	1	1uF	C1005X5R1E105K050BC	TDK	CAP, CERM, 1 µF, 25 V, +/- 10%, X5R, 0402	0402
7	C7, C8	2	4.7uF	GRM155R60J475ME47D	MuRata	CAP, CERM, 4.7 µF, 6.3 V, +/- 20%, X5R, 0402	0402
8	C9	1	10uF	C0603C106M9PACTU	Kemet	CAP, CERM, 10 µF, 6.3 V, +/- 20%, X5R, 0603	0603
9	C10	1	22uF	GRM21BR60J226ME39L	MuRata	CAP, CERM, 22 µF, 6.3 V, +/- 20%, X5R, 0805	0805
10	C11	1	0.01uF	CGA2B3X7S2A103K050BB	TDK	CAP, CERM, 0.01 µF, 100 V, +/- 10%, X7S, AEC-Q200 Grade 1, 0402	0402
11	C12, C13	2	22uF	EEE-FK1J220XP	Panasonic	CAP, AL, 22 µF, 63 V, +/- 20%, 1.2 ohm, AEC-Q200 Grade 2, SMD	SMT Radial D8
12	C16, C17	2	0.068uF	C1608X7S2A683K080AB	TDK	CAP, CERM, 0.068 µF, 100 V, +/- 10%, X7S, 0603	0603
13	C18	1	3300pF	GRM155R71H332KA01D	MuRata	CAP, CERM, 3300 pF, 50 V, +/- 10%, X7R, 0402	0402
14	C19	1	0.033uF	GRM155R61C333KA01D	MuRata	CAP, CERM, 0.033 µF, 16 V, +/- 10%, X5R, 0402	0402
15	C20	1	100pF	CC0402KRX7R9BB101	Yageo America	CAP, CERM, 100 pF, 50 V, +/- 10%, X7R, 0402	0402
16	C21	1	4.7uF	C1005X5R1A475M050BC	TDK	CAP, CERM, 4.7 µF, 10 V, +/- 20%, X5R, 0402	0402
17	C22	1	0.1uF	GRM155R61E104KA87D	MuRata	CAP, CERM, 0.1 µF, 25 V, +/- 10%, X5R, 0402	0402
18	C23	1	47uF	GRM21BR60J476ME15L	MuRata	CAP, CERM, 47 µF, 6.3 V, +/- 20%, X5R, 0805	0805
19	C24	1	22uF	GRM21BR61A226ME44L	MuRata	CAP, CERM, 22 µF, 10 V, +/- 20%, X5R, 0805	0805
20	C25, C26	2	1uF	C1005X5R1A105K050BB	TDK	CAP, CERM, 1 µF, 10 V, +/- 10%, X5R, 0402	0402
21	C27, C28	2	0.1uF	160R07X104KV4T	Johanson Technology	CAP, CERM, 0.1 µF, 16 V, +/- 10%, X5R, 0402	0402
22	C29	1	0.015uF	CGA2B2X7R1E153K050BA	TDK	CAP, CERM, 0.015 µF, 25 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0402	0402
23	D1	1	200V	DF1502S-T	Diodes Inc.	Diode, Switching-Bridge, 200 V, 1.5 A, DF-S	DF-S
24	D2	1	12V	MMSZ5242BS-7-F	Diodes Inc.	Diode, Zener, 12 V, 200 mW, SOD-323	SOD-323
25	D3	1	Green	150060GS75000	Würth Elektronik	LED, Green, SMD	LED_0603
26	H1, H2, H3, H4	4		NY PMS 440 0025 PH	B&F Fastener Supply	Machine Screw, Round, #4-40 x 1/4, Nylon, Philips panhead	Screw
27	H5, H6, H7, H8	4		1902C	Keystone	Standoff, Hex, 0.5"L #4-40 Nylon	Standoff
28	J1	1		ZX62WRD-B-5PC	Hirose Electric Co. Ltd.	Connector, Receptacle, Micro-USB Type B, R/A, Top Mount SMT	Micro USB-B receptacle
29	J2	1		39357-0002	Molex	Terminal Block, 3.5 mm, 2x1, Tin, TH	Terminal Block, 3.5 mm, 2x1, TH
30	J3	1		1725669	Phoenix Contact	Terminal Block, 3x1, 2.54 mm, TH	Terminal Block, 3x1, 2.54 mm, TH
31	J4	1		1725672	Phoenix Contact	Terminal Block, 4x1, 2.54 mm, Green, TH	Terminal Block, 4x1, 2.54 mm, TH
32	L1	1	100uH	DR74-101-R	Coiltronics	Inductor, Shielded Drum Core, Ferrite, 100 µH, 0.86 A, 0.383 ohm, SMD	DR74
33	L2	1	1uH	XFL3012-102MEB	Coilcraft	Inductor, Shielded, Composite, 1 µH, 2.5 A, 0.04 ohm, SMD	3x1.2x3mm
34	LBL1	1		THT-14-423-10	Brady	Thermal Transfer Printable Labels, 0.650" W x 0.200" H - 10,000 per roll	PCB Label 0.650"H x 0.200"W
35	Q1	1	60V	IRLML0060TRPBF	International Rectifier	MOSFET, N-CH, 60 V, 2.7 A, SOT-23	SOT-23
36	R1	1	1.2k	ERJ-6GEY1J122V	Panasonic	RES, 1.2 k, 5%, 0.125 W, 0805	0805
37	R2	1	150k	CRCW0402150KFKED	Vishay-Dale	RES, 150 k, 1%, 0.063 W, 0402	0402
38	R3	1	453k	CRCW0402453KFKED	Vishay-Dale	RES, 453 k, 1%, 0.063 W, 0402	0402
39	R4	1	100k	CRCW0402100KJNED	Vishay-Dale	RES, 100 k, 5%, 0.063 W, 0402	0402
40	R5	1	226k	CRCW0402226KFKED	Vishay-Dale	RES, 226 k, 1%, 0.063 W, 0402	0402
41	R6, R9	2	33.2k	CRCW040233K2FKED	Vishay-Dale	RES, 33.2 k, 1%, 0.063 W, 0402	0402
42	R7	1	2.00k	CRCW04022K00FKED	Vishay-Dale	RES, 2.00 k, 1%, 0.063 W, 0402	0402
43	R11, R12, R13, R34	4	0	ERJ-6GEY0R00V	Panasonic	RES, 0, 5%, 0.125 W, 0805	0805
44	R14, R32, R33	3	0	CRCW04020000Z0ED	Vishay-Dale	RES, 0, 5%, 0.063 W, 0402	0402

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
45	R16	1	10k	CRCW040210K0JNED	Vishay-Dale	RES, 10 k, 5%, 0.063 W, 0402	0402
46	R17	1	100	CRCW0402100RJNED	Vishay-Dale	RES, 100, 5%, 0.063 W, 0402	0402
47	R18	1	178k	CRCW0402178KFKED	Vishay-Dale	RES, 178 k, 1%, 0.063 W, 0402	0402
48	R19	1	249k	CRCW0402249KFKED	Vishay-Dale	RES, 249 k, 1%, 0.063 W, 0402	0402
49	R20	1	39.2k	CRCW040239K2FKED	Vishay-Dale	RES, 39.2 k, 1%, 0.063 W, 0402	0402
50	R21	1	475k	CRCW0402475KFKED	Vishay-Dale	RES, 475 k, 1%, 0.063 W, 0402	0402
51	R22	1	309k	CRCW0402309KFKED	Vishay-Dale	RES, 309 k, 1%, 0.063 W, 0402	0402
52	R23	1	100k	CRCW0402100KFKED	Vishay-Dale	RES, 100 k, 1%, 0.063 W, 0402	0402
53	R24, R25, R26	3	20.0k	CRCW040220K0FKED	Vishay-Dale	RES, 20.0 k, 1%, 0.063 W, 0402	0402
54	R27	1	22.1k	CRCW040222K1FKED	Vishay-Dale	RES, 22.1 k, 1%, 0.063 W, 0402	0402
55	R28	1	200k	CRCW0402200KFKED	Vishay-Dale	RES, 200 k, 1%, 0.063 W, 0402	0402
56	R29	1	1.00	CRCW04021R00FKED	Vishay-Dale	RES, 1.00, 1%, 0.063 W, 0402	0402
57	R30, R31	2	3.0k	CRCW04023K00JNED	Vishay-Dale	RES, 3.0 k, 5%, 0.063 W, 0402	0402
58	R35	1	0	ERJ-3GEY0R00V	Panasonic	RES, 0, 5%, 0.1 W, 0603	0603
59	TP1, TP3, TP7, TP9, TP10, TP11, TP12	7		5005	Keystone	Test Point, Compact, Red, TH	Red Compact Testpoint
60	TP2, TP4, TP5, TP16, TP17	5		5007	Keystone	Test Point, Compact, White, TH	White Compact Testpoint
61	TP18, TP19	2		5006	Keystone	Test Point, Compact, Black, TH	Black Compact Testpoint
62	U1	1		TPD2E2U06DRLR	Texas Instruments	DUAL CHANNEL HIGH SPEED ESD PROTECTION DEVICE, DRL0005A	DRL0005A
63	U2	1		LM5166DRCR	Texas Instruments	3.0-V to 65-V Input, 500-mA Synchronous Buck Converter with Ultra-Low IQ, DRC0010J	DRC0010J
64	U3, U4	2		TPS27081ADDCR	Texas Instruments	1.2V - 8V, 3A PFET High Side Load Switch with Level Shift & Adjustable Slew Rate Control, DDC0006A	DDC0006A
65	U5	1		BQ24072RGTT	Texas Instruments	USB-Friendly Li-Ion Battery Charger and Power-Path Management IC, Vout 200 mV above Vbat, 4.3 V, -40 to 85 degC, 16-pin QFN (RGT), Green (RoHS & no Sb/Br)	RGT0016C
66	U6	1		TLV62080DSGR	Texas Instruments	1.2A High Efficient Step Down Converter in 2x2mm SON Package, DSG0008A	DSG0008A
67	U7	1		LM2903D	Texas Instruments	Dual Comparator, D0008A	D0008A
68	U8	1		TPD1E10B06DPYR	Texas Instruments	ESD in 0402 Package with 10 pF Capacitance and 6 V Breakdown, 1 Channel, -40 to +125 degC, 2-pin X2SON (DPY), Green (RoHS & no Sb/Br)	DPY0002A
69	C5	0	47pF	GRM1555C1H470FA01D	MuRata	CAP, CERM, 47 pF, 50 V, +/- 1%, C0G/NP0, 0402	0402
70	FID1, FID2, FID3, FID4, FID5, FID6	0		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	Fiducial
71	R8	0	2.00k	CRCW04022K00FKED	Vishay-Dale	RES, 2.00 k, 1%, 0.063 W, 0402	0402
72	R10	0	5.1k	CRCW04025K10JNED	Vishay-Dale	RES, 5.1 k, 5%, 0.063 W, 0402	0402
73	R15	0	10k	CRCW040210K0JNED	Vishay-Dale	RES, 10 k, 5%, 0.063 W, 0402	0402

IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Designer(s)") who are developing systems that incorporate TI products. TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.

TI's provision of reference designs and any other technical, applications or design advice, quality characterization, reliability data or other information or services does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such reference designs or other items.

TI reserves the right to make corrections, enhancements, improvements and other changes to its reference designs and other items.

Designer understands and agrees that Designer remains responsible for using its independent analysis, evaluation and judgment in designing Designer's systems and products, and has full and exclusive responsibility to assure the safety of its products and compliance of its products (and of all TI products used in or for such Designer's products) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to its applications, it has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any systems that include TI products, Designer will thoroughly test such systems and the functionality of such TI products as used in such systems. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

Designers are authorized to use, copy and modify any individual TI reference design only in connection with the development of end products that include the TI product(s) identified in that reference design. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of the reference design or other items described above may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS AND OTHER ITEMS DESCRIBED ABOVE ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNERS AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS AS DESCRIBED IN A TI REFERENCE DESIGN OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

TI's standard terms of sale for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>) apply to the sale of packaged integrated circuit products. Additional terms may apply to the use or sale of other types of TI products and services.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2016, Texas Instruments Incorporated