

Filename: gtg5cj5k.xlsx
 Variant: 001
 Generated: 2/28/2024 10:13 AM
 TID #: TIDA-050073



TIDA-050073 REV A Bill of Materials

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	IPCB1	1		TIDA-050073	Any	Printed Circuit Board	
2	C1, C5, C9	3	0.1uF	C0603C104K5RACAUTO	Kemet	CAP, CERM, 0.1 μ F, 50 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0603	603
3	C2	1	47uF	GRM31CR61A476KE15L	MuRata	CAP, CERM, 47 uF, 10 V, +/- 10%, X5R, 1206	1206
4	C3, C13	2	22uF	C3216X5R1V226M160AC	TDK	CAP, CERM, 22 uF, 35 V, +/- 20%, X5R, 1206	1206
5	C7, C8	2	10uF	CGA5L1X7R1H106K160AC	TDK	CAP, CERM, 10 μ F, 50 V, +/- 10%, X7R, AEC-Q200 Grade 1, 1206	1206
6	C10	1	0.033uF	06035C333JAT2A	AVX	CAP, CERM, 0.033 uF, 50 V, +/- 5%, X7R, 0603	603
7	C11	1	470pF	C0603C471K5RACTU	Kemet	CAP, CERM, 470 pF, 50 V, +/- 10%, X7R, 0603	603
8	C12	1	0.01uF	C0603C103J5RACTU	Kemet	CAP, CERM, 0.01 uF, 50 V, +/- 5%, X7R, 0603	603
9	C17, C18	2	470pF	GRM1555C1H471JA01D	MuRata	CAP, CERM, 470 pF, 50 V, +/- 5%, C0G/NP0, 0402	402
10	C19	1	2200pF	GRM155R71H222KA01D	MuRata	CAP, CERM, 2200 pF, 50 V, +/- 10%, X7R, 0402	402
11	D1	1	5.1V	MMSZ5231BS-7-F	Diodes Inc.	Diode, Zener, 5.1 V, 200 mW, SOD-323	SOD-323
12	FB1	1		BLM18SN220TN1D	Murata	Chip Ferrite Bead Array, 0603, 22 Ω @ 100MHz, \pm 7 Ω , 0.004 Ω , 8A	603
13	J1, J2	2		ED120/2DS	On-Shore Technology	Terminal Block, 5.08 mm, 2x1, Brass, TH	2x1 5.08 mm Terminal Block
14	J3, J4	2		6.0312E+13	Würth Electronics	SMA Connector Jack, Female Socket 50Ohm Through Hole Solder	CONN_SMA_PTH
15	JP1, JP2	2		PBC02SAAN	Sullins Connector Solutions	Header, 100mil, 2x1, Gold, TH	Sullins 100mil, 1x2, 230 mil above insulator
16	JP3	1		PEC03SAAN	Sullins Connector Solutions	Header, 100mil, 3x1, Tin, TH	Header, 3 PIN, 100mil, Tin
17	L1	1	2.2uH	74437349022	Würth Elektronik	Inductor, Shielded Drum Core, Powdered Iron, 2.2 uH, 7.5 A, 0.0112 ohm, SMD	7.30x4.80x6.60mm
18	R1, R3, R6, R7, R10, R11	6	0	RC0603JR-070RL	Yageo	RES, 0, 5%, 0.1 W, 0603	603
19	R5	1	10.0k	RC0603FR-0710KL	Yageo	RES, 10.0 k, 1%, 0.1 W, 0603	603
20	R8, R9	2	49.9k	RC0603FR-0749K9L	Yageo	RES, 49.9 k, 1%, 0.1 W, 0603	603
21	R12	1	4.99k	RC0603FR-074K99L	Yageo	RES, 4.99 k, 1%, 0.1 W, 0603	603
22	SH-JP1, SH-JP2, SH-JP3	3	1x2	SNT-100-BK-G	Samtec	Shunt, 100mil, Gold plated, Black	Shunt
23	TP1, TP3, TP18	3		5010	Keystone	Test Point, Multipurpose, Red, TH	Red Multipurpose Testpoint
24	TP2, TP4, TP5, TP6	4		1502-2	Keystone	Terminal, Turret, TH, Double	Keystone1502-2
25	TP7, TP13, TP14, TP15, TP16, TP17	6		5011	Keystone	Test Point, Multipurpose, Black, TH	Black Multipurpose Testpoint
26	TP8, TP10, TP11	3		5014	Keystone	Test Point, Multipurpose, Yellow, TH	Yellow Multipurpose Testpoint
27	U1	1		TPS62933FDRL	Texas Instruments	3.8-V to 30-V, 3-A Synchronous Buck Converter in a SOT583 Package	SOT583
28	C4, C14, C15	0	22uF	C3216X5R1V226M160AC	TDK	CAP, CERM, 22 uF, 35 V, +/- 20%, X5R, 1206	1206
29	C6	0	10uF	CGA5L1X7R1H106K160AC	TDK	CAP, CERM, 10 μ F, 50 V, +/- 10%, X7R, AEC-Q200 Grade 1, 1206	1206
30	C16	0	2200pF	GRM155R71H222KA01D	MuRata	CAP, CERM, 2200 pF, 50 V, +/- 10%, X7R, 0402	402
31	FID1, FID2, FID3	0		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	N/A
32	R4	0	4.99k	RC0603FR-074K99L	Yageo	RES, 4.99 k, 1%, 0.1 W, 0603	603

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on [ti.com](https://www.ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2024, Texas Instruments Incorporated